

# **EK-*i*/EW-*i* Series**

## ***Compact Balances***

**EK-120*i* / EK-200*i* / EK-300*i* / EK-600*i***

**EK-1200*i* / EK-2000*i* / EK-3000*i* / EK-6000*i* / EK-12K*i***

**EW-150*i* / EW-1500*i* / EW-12K*i***

## **INSTRUCTION MANUAL**

---



**© 2002 A&D Company Ltd. All rights reserved.**

No part of this publication may be reproduced, transmitted, transcribed, or translated into any language in any form by any means without the written permission of A&D Company Ltd.

The contents of this manual and the specifications of the instrument covered by this manual are subject to change for improvement without notice.

### **COMPLIANCE WITH FCC RULES**

Please note that this equipment generates, uses and can radiate radio frequency energy. This equipment has been tested and has been found to comply with the limits of Class A computing device pursuant to Subpart J of Part 15 of FCC rules. These rules are designed to provide reasonable protection against interference when the equipment is operated in a commercial environment. If this unit is operated in a residential area it may cause some interference and under these circumstances the user would be required to take, at his own expense, whatever measures are necessary to eliminate the interference.

(FCC = Federal Communications Commission in the U.S.A.)

#### **Note**

Under some ambient electromagnetic conditions, this equipment may be affected by the electromagnetic interference.

 This is a hazard alert mark.

---

# CONTENTS

---

<b>1. INTRODUCTION .....</b>	<b>3</b>
<b>2. UNPACKING.....</b>	<b>3</b>
<b>3. PART NAMES AND FUNCTIONS.....</b>	<b>4</b>
<b>4. SETTING UP .....</b>	<b>5</b>
4-1. Setting up your balance .....	5
4-2. Power source.....	5
<b>5. OPERATION.....</b>	<b>6</b>
5-1. Turn the power ON and OFF.....	6
5-2. LCD backlight .....	6
5-3. Units .....	7
5-4. Selecting a weighing unit .....	8
5-5. Basic operation.....	8
5-6. Weighing range for the EW- <i>i</i> series .....	9
5-7. Counting mode (pcs).....	10
5-8. Percent mode (%).....	11
<b>6. COMPARATOR.....</b>	<b>12</b>
6-1. Setting example .....	12
<b>7. CALIBRATION .....</b>	<b>14</b>
7-1. Calibration using a weight .....	14
7-2. Gravity acceleration correction.....	15
<b>8. FUNCTIONS.....</b>	<b>16</b>
8-1. Key operation.....	17
8-2. Entering the function setting mode.....	17
8-3. Setting example .....	17
8-4. Storing weighing units.....	18
8-5. Function list .....	19
<b>9. RS-232C SERIAL INTERFACE.....</b>	<b>21</b>
9-1. Interface specifications .....	22
9-2. Data format .....	22
9-3. Data output mode .....	23
9-4. Command mode.....	24
<b>10. ID NUMBER AND GLP .....</b>	<b>24</b>
10-1. Setting the ID number.....	25
10-2. Output example.....	25

10-3. Output procedure for the “Calibration report” .....	27
10-4. Output procedure for the “Calibration test report” .....	28
10-5. Output procedure for the “Start block” and “End block” .....	30
<b>11. OPTIONS .....</b>	<b>31</b>
11-1. OP-04 Comparator relay output and buzzer .....	32
11-2. OP-07 Underhook assembly .....	33
11-3. OP-09 Rechargeable battery pack (Ni-MH) .....	33
11-4. OP-12 Carrying case.....	34
<b>12. MAINTENANCE .....</b>	<b>34</b>
12-1. Notes on maintenance.....	34
12-2 Error codes .....	35
<b>13. SPECIFICATIONS.....</b>	<b>36</b>
13-1. EK- <i>i</i> series .....	36
13-2. EW- <i>i</i> series .....	37
13-3. Other weighing units .....	38
13-4. Dimensions .....	39
<b>GRAVITY ACCELERATION MAP.....</b>	<b>39</b>

---

# 1. INTRODUCTION

---

This manual describes how this balance works and how to get the most out of it in terms of performance.

EK-*i* and EW-*i* series balances have the following features:


- ❑ The EK-*i* series are high resolution type electronic balances having a resolution of 1/6,000 ~ 1/30,000.
- ❑ The EW-*i* series are triple range balances and each range has a resolution of 1/3,000.
- ❑ Both series have similar functions like a counting function, % function and a comparator function.
- ❑ The backlight LCD will help with use in a dimly lighted place.
- ❑ The standard RS-232C serial interface can be connected with a printer or personal computer.
- ❑ Using a serial interface, Good Laboratory Practice (GLP) data can be obtained.
- ❑ With the optional rechargeable battery pack (OP-09), the balance can be used for cordless operation.

---


# 2. UNPACKING

---

When unpacking, check whether all of the following items are included:



Main unit



AC adapter




**Please confirm that the AC adapter type is correct for your local voltage and receptacle type.**

Instruction manual



# 3. PART NAMES AND FUNCTIONS



- |  |   |  |   |
|--|---|--|---|
|  | Turns the power on or off.  |  | Outputs the weight value to printer.            |
|  | <p>Held down to enter the function setting mode.</p> <p>Weighing mode (EW-<i>i</i> only):<br/>Changes the weighing range (when rng 0 is selected).</p> <p>pcs mode:<br/>Enters the sample unit weight storing mode.</p> <p>% mode:<br/>Enters the 100% weight storing mode.</p> |  | Switches the weighing unit (the weighing mode). |
|  | Clears the display to zero.   |  |   |

---

## 4. SETTING UP

---

### 4-1. Setting up your balance

1. Place the weighing pan on the main unit as shown on the previous page.
2. Adjust the level of the balance using the leveling feet. Use the spirit level to confirm. The bubble should be in the center of the circle.
3. Calibrate your balance before use. (See "7. CALIBRATION")

#### Balance location

To measure correctly, to keep the balance in good condition, and to prevent hazards, observe the following:

- Do not install the balance in locations that are subject to excessive dust, breezes, vibration, large temperature fluctuations, condensation, or that may have magnetic fields.
- Do not install the balance on a surface that is soft or that may cause the balance level to shift.
- Do not install the balance in direct sunshine.
- Do not install the balance near heaters or air conditioners.
- Do not use an unstable AC power source.
- Do not install the balance in a place where combustible or corrosive gases may exist.
- Allow the balance to reach equilibrium with the ambient temperature before use.
- Switch the power ON at least half an hour before use so that the balance can warm up.
- When the balance is installed for the first time, or the balance has been moved, carry out calibration as described in "7. CALIBRATION."

### 4-2. Power source

For the power source, the AC adapter or the rechargeable battery pack (OP-09: Optional item) is available.

#### When using the AC adapter

Use a stable power source. To use the AC adapter, insert the AC adapter plug into the AC adapter jack on the EK/EW-*i*.

#### When using the rechargeable battery pack (OP-09)

Insert the rechargeable battery pack into the main unit.

The balance can be used continuously for about 9 hours using the battery pack.

- If "Lb0" is displayed when using the battery pack, immediately stop using it, and recharge the battery pack or use the AC adapter.***
- See "11-3 OP-09 Rechargeable battery pack", for instructions to install and charge the battery pack.***
- Be sure to charge the battery pack before using it for the first time.***

---

## 5. OPERATION

---

### 5-1. Turn the power ON and OFF

1. Press the  ON/OFF  key to turn the power ON.



All of the symbols are displayed as shown above.  
(About units: Only the units available will be displayed.)

The display turns off except for a weighing unit and the decimal point.  
The balance waits for the weighing data to become stable, and zero will be displayed with the ZERO mark (power-on zero).

The range for power-on zero is within  $\pm 10\%$  of the weighing capacity around the calibrated zero point.

If the power is switched ON while there is a load beyond this range, the balance will be tared to zero and the NET mark and the ZERO mark turn on.

2. Pressing the  ON/OFF  key again, and the power will be switched OFF.

#### **Auto-power off function**

*It is possible to have the power automatically switched OFF, if zero is displayed for approximately 5 minutes. See "8-5. Function list" and set the function "poff".*

### 5-2. LCD backlight


The LCD backlight will turn on when the weight value changes more than 4 display digits or any key operation is done. When the weight data becomes and stays stable for some moment, the backlight will automatically turn off. There is also a setting that the backlight is always on or off. For details, see the function setting "I tup" of "Function list".



## 5-3. Units

The most common unit of weight used around the world is the gram, but there is often a need to shift to alternative units specific to the country where the balance is used or to select modes such as counting or percent.

The units and the order they appear in the display are as follows:



Among the units, those available for the user have been set at the factory before shipping.

The unit can be selected in the function setting mode. The order of the units available is the same as above, while skipping the units that are not available.

Some units are not available for higher or lower capacity models. For details, see “13. SPECIFICATIONS”

### □ Note

*It is possible to store only the units that will be actually used from the units available. It is also possible to specify the display unit that will be shown first when the power is switched ON. For details, see “8-4. Storing weighing units”.*

### Conversion table

Units	Name	Conversion to gram
oz	Ounce (avoir)	28.349523125 g
lb	Pound (UK)	453.59237 g
ozt	Troy ounce	31.1034768 g
ct	Metric carat	0.2 g
mom	momme	3.75 g
dwt	Pennyweight	1.55517384 g
GN	Grain (UK)	0.06479891 g
tl	tael (Hong Kong general, Singapore)	37.7994 g


### □ Note

*The unit “tl (tael)” is for special versions only.*


## 5-4. Selecting a weighing unit

Press the **MODE** key to select a unit.

The following sections are a description of the three common units: g (gram mode), pcs (counting mode), and % (percent mode).






Each pressing switches the units available in the order described on the previous page.



## 5-5. Basic operation

1. Select a weighing unit.
2. When the display doesn't show zero, press the **RE-ZERO** key to set the display to zero.
3. When using a tare (container), place the container on the weighing pan, and press the **RE-ZERO** key to set the display to zero.
4. Place the object to be weighed on the pan or in the container.  
Wait for the stability mark (○) to be displayed and read the value.
5. Remove the object from the pan.



### □ Note

*The RE-ZERO key will zero the balance if the weight is within  $\pm 2\%$  of the weighing capacity around the power-on zero point. The ZERO mark ◀ turns on. When the weight exceeds  $+2\%$  of the weighing capacity, it will be subtracted to zero as a tare weight. In this case the ZERO and NET marks turn on.*

## Precautions during operation

- Make sure that the stability mark is on whenever reading or storing a value.
- Do not press the keys with a sharp object such as a pencil.
- Do not apply a shock or a load to the pan that is beyond the weighing capacity.
- Keep the balance free from foreign objects such as dust or liquid.
- Calibrate the balance periodically to keep weighing accuracy. (See "7. CALIBRATION".)

## 5-6. Weighing range for the EW-i series

- The EW-i series have three weighing ranges, and the display shows which range the weight value belongs to with the mark R1, R2 or R3.
- There is a function setting to select how the weighing range changes.
- Select from automatic range (rng 1), manual range (rng 0) or fixed range (rng 2 to 4).

### Operation

Function setting	Operation
rng 1	<p>Automatic range</p> <ul style="list-style-type: none"> <li><input type="checkbox"/> When the weight value exceeds the maximum value of the range, the weighing range changes automatically from a lower to a higher weighing range.</li> <li><input type="checkbox"/> When there is nothing on the weighing pan and the display shows zero with the ZERO mark, the weighing range changes from a higher to the lowest range.</li> <li><input type="checkbox"/> When the <b>RE-ZERO</b> key is pressed in a higher range, the balance will be tared and zeroed and the weighing range becomes the lowest range.</li> </ul>
rng 0	<p>Manual range</p> <ul style="list-style-type: none"> <li><input type="checkbox"/> Press the <b>SAMPLE</b> key when the display shows a weight value (neither counting nor % display). The weighing range changes to a higher range at any load.</li> <li><input type="checkbox"/> Press the <b>SAMPLE</b> key to change from a higher to the lowest range, when there is nothing on the weighing pan and the display shows zero with the ZERO mark.</li> <li><input type="checkbox"/> When the <b>RE-ZERO</b> key is pressed in a higher range, the balance will be tared and zeroed and the weighing range becomes the lowest range. If the weight of the object is not more than 2% of the weighing capacity, the <b>RE-ZERO</b> key doesn't tare, but zeroes the balance and the weighing range doesn't change. Press the <b>SAMPLE</b> key to change the weighing range at zero display.</li> </ul>
rng 2 to 4	<p>Fixed range</p> <ul style="list-style-type: none"> <li><input type="checkbox"/> The weighing range is fixed. Set the function to the weighing range according to the purpose.</li> </ul>

## 5-7. Counting mode (pcs)

Determines the number of objects in a sample. Calculates the reading, using the basic sample unit weight, and determines how many pieces are contained.

### Selecting the counting mode

1. Press the **MODE** key to select **PCS**.

(PCS :pieces)

### Storing the sample unit

2. Press the **SAMPLE** key to enter the sample unit weight storing mode.
3. To select the number of samples, press the **SAMPLE** key. It may be set to 5, 10, 25, 50, or 100.
4. Place a tare container on the weighing pan, and press the **RE-ZERO** key. Confirm that the right side of the number of samples shows zero.
5. Place the number of samples specified on the pan. In this example, 25 pieces.
6. Press the **PRINT** key to calculate and store the unit weight. Remove the sample. The balance is set to count objects with this unit weight.




### Counting the objects

7. Place the objects to be counted on the pan.




### Counting mode using the ACAI function

ACAI™ (Automatic Counting Accuracy Improvement) is a function that improves the accuracy of the unit weight by increasing the number of samples as the counting process proceeds.




8. If a few more samples are added, the ACAI mark is displayed. (To prevent an error, add three or more. The ACAI mark will not be displayed if overloaded.)



Each pressing switches the number of samples.



Confirm the display




9. The balance re-calculates the unit weight while the ACAI mark is blinking. Do not touch the balance or samples on the pan until the ACAI mark turns off.
10. Counting accuracy is improved when the ACAI mark turns off. Each time the above operation is performed, a more accurate unit weight will be obtained. There is no definite upper limit of ACAI range for the number of samples exceeding 100. Try to add the similar number of samples as displayed.

## 5-8. Percent mode (%)

Displays the weighing value in percentage compared to the reference (100%) weight.


### Selecting the percent mode

1. Press the **MODE** key to select **%**. (%:percent)




### Storing the reference (100%) weight


2. Press the **SAMPLE** key to enter the reference weight storing mode.





3. Press the **RE-ZERO** key to display **100 0%**.



4. Place the sample to be set as the reference weight on the pan.





5. Press the **PRINT** key to store the reference weight. Remove the sample.



### Reading the percentage

6. Place the object to be compared to the reference weight on the pan. The displayed percentage is based on 100% of the reference weight.



## 6. COMPARATOR

The results of the comparison are indicated by HI, OK or LO on the display.  
The comparison is as follows:

$$LO < \text{Lower limit value} \leq OK \leq \text{Upper limit value} < HI$$

Operating conditions (see the function setting "Cp"):

- No comparison (comparator function disabled).
  - Compares all data.
  - Compares all stable data.
  - Compares plus data greater than +4d.
  - Compares stable plus data greater than +4d.
  - Compares all data greater than +4d or less than -4d.
  - Compares stable data greater than +4d or less than -4d.
- d = the smallest display division

The upper limit and lower limit numerical values are common to each of the weighing, counting and percent mode. The example for EK-1200i/2000i/3000i is as follows.



Upper limit value "001010": "101.0g" "1010pcs" "101.0%"  
Lower limit value "000990": "99.0g" "990pcs" "99.0%"

### 6-1. Setting example

This example will be "Compares plus data greater than +4d".

#### Selecting a comparison mode

1. Press and hold the **SAMPLE** key to display **func**.  
(If the comparison mode is already set, press the **SAMPLE** key to go to "Entering the upper and lower limit values".)
2. Press the **PRINT** key, then the balance displays **poff X**.
3. Press the **SAMPLE** key several times to display **Cp X**.
4. Press the **RE-ZERO** key several times to display **Cp 3**.
5. Press the **PRINT** key to store the settings.  
**Cp Hi** appears after **end**.



## Entering the upper and lower limit values

6. With **Cp Hi** displayed, press the **PRINT** key. Enter the upper limit value using the following keys.


**SAMPLE** key To select the digit blinking to change.

**RE-ZERO** key To set the value of the digit selected. Hold down the key to switch the sign “+” and “-”. (“N” designates a negative value.)

**PRINT** key To store the value and proceed to the next step.

**MODE** key To cancel the value and proceed to the next step.

Cp Hi



000000

Set using the relevant keys

001234 N



To store

7. With **Cp Lo** displayed, press the **PRINT** key. Enter the lower limit value using the following keys.


**SAMPLE** key To select the digit blinking to change.

**RE-ZERO** key To set the value of the digit selected. Hold down the key to switch the sign “+” and “-” (see step 6).

**PRINT** key To store the value and proceed to the next step.

**MODE** key To cancel the value and proceed to the next step.


Cp Lo



000000

Set using the relevant keys

001230




To store

8. Press the **PRINT** key. **Uni t** appears after **end**.

end

Uni t

9. Press the **MODE** key to return to the weighing mode.




Returns to the weighing mode

# 7. CALIBRATION

This function adjusts the balance for accurate weighing. Perform a calibration in the following cases.

- When the balance is first used.
- When the balance has been moved.
- When the ambient environment has changed.
- For regular calibration.

Press and lower down the calibration switch cover



## 7-1. Calibration using a weight

1. Warm up the balance for at least half an hour with nothing on the pan.
2. Press and hold the calibration (CAL) switch until **Cal** appears, and release the switch.
3. The balance displays **Cal 0**.

To change the calibration weight value, proceed to step 4.

To use the calibration weight value in the balance memory, proceed to step 5.


4. Press the **SAMPLE** key. The display shows the calibration weight value in "gram" that is stored in the balance. Use the following keys to change the value.

- |                    |   |
|--------------------|---|
| <b>SAMPLE</b> key  | To select the digit blinking to change.   |
| <b>RE-ZERO</b> key | To set the value of the digit selected.   |
| <b>PRINT</b> key   | To store the value and return to step 3.  |
| <b>MODE</b> key    | To cancel the value and return to step 3. |

Press and hold the CAL switch.



Release the CAL switch.




Set the weight using the relevant keys.






5. At step 3, pressing the **PRINT** key weighs the zero-point value. Do not touch the pan during weighing.



6. Place the calibration weight with the same value as displayed on the pan. Press the **PRINT** key to weigh it. Do not touch the pan during weighing.



7. **end** appears.  
Remove the weight from the pan, and press the CAL switch or **MODE** key to return to the weighing mode.



**Note**

*The value set in step 4 is stored in memory even when the power is switched off.*

*If the balance is to be moved to other places, set the gravity acceleration value of the area where the calibration using a weight is to be done, and calibrate the balance according to the procedure above. See the next section to set the value.*

## 7-2. Gravity acceleration correction

When the balance is first used or has been moved to a different place, it should be calibrated using a calibration weight.

But if the calibration weight cannot be prepared, the gravity acceleration correction will compensate the balance. Change the gravity acceleration value of the balance to the value of the area where the balance will be used. See the gravity acceleration map appended to the end of this manual.

❑ **Note**

**Gravity acceleration correction is not required when the balance is calibrated using a calibration weight at the place where the balance is to be used.**

1. Press and hold the calibration (CAL) switch until **Cal** appears, and release the switch.



Press and hold the CAL switch.



2. The balance displays **Cal 0**.

Release the CAL switch.



3. Press the **RE-ZERO** key.

The display shows the gravity acceleration value stored in the balance.



Use the following keys to change the value.

**SAMPLE** key To select the digit blinking to change.

**RE-ZERO** key To set the value of the digit selected.

**PRINT** key To store the value and return to step 2.


**MODE** key To cancel the value and return to step 2.



Set the value using the relevant keys.



To store




4. After setting the value, press the **PRINT** key.

**Cal 0** is displayed again.

5. If it is necessary to calibrate the balance using a calibration weight, go to step 4 of 7-1.

To finish the setting, press **MODE** key.



Returns to the weighing mode


6. **end** appears and the balance returns to the weighing mode.

---

## 8. FUNCTIONS

---


## 8-1. Key operation



## 8-2. Entering the function setting mode

In the weighing mode, press and hold the **SAMPLE** key to enter the function setting mode and display **func**. Each time the **SAMPLE** key is pressed, the class appears one after another.


Once the class is selected, the set items are available for selection. (See “Function list”.)



## 8-3. Setting example

To set auto power-off function to “Enabled”, and the ACAI function to “Disabled”.

1. Press and hold the **SAMPLE** key to display **func**.



Press and hold

**func**

2. Press the **PRINT** key. The balance displays **poff 0**.



**poff 0**

3. Press the **RE-ZERO** key to display **poff 1**.



Each pressing switches the parameter

**poff 1**

4. Press the **SAMPLE** key several times to display **aCai 1**.



To confirm

**aCai 1**

5. Press the **RE-ZERO** key to select **aCai 0**.



Each pressing switches the parameter

**aCai 0**

6. Press the **PRINT** key to store the parameters. **Cp Hi** appears after **end**.




To store

**end**

**Cp Hi**

7. Press the **MODE** key to return to the weighing mode.



Returns to the weighing mode

## 8-4. Storing weighing units

It is possible to store the weighing units that will be actually used from the units available. For the units available, see "5-3. Units"

Select and store the weighing units as described below:

1. Press and hold the **SAMPLE** key to display **func**.



**func**

2. Press the **SAMPLE** key several times to display **Uni t**.




**Uni t**

3. Press the **PRINT** key.



**Uni t g**

4. Press the **SAMPLE** key to select a weighing unit.



Each pressing switches the units available in the order described on 5-3.

**Uni t**

5. Press the **RE-ZERO** key to store the weighing unit.



To store

6. Repeat steps 4. and 5. to store all weighing units to be used.




To confirm

7. Press the **PRINT** key. **id** appears after **end**.

**end**

**id**

8. Press the **MODE** key to return to the weighing mode



Returns to the weighing mode

**Note**

*When the balance is switched on, it starts with the unit that was stored first at step 5.*

### 8-5. Function list

Class	Item	Parameter	Description	
<b>func</b>	<b>poff</b>	♦ <b>0</b>	Auto power-off disabled	Automatically

	Auto power-off	<b>1</b>	Auto power-off enabled	power off
<b>rng</b> Range		<b>0</b>	Manual range change	Range change setting for EW-i series
		♦ <b>1</b>	Automatic range change	
		<b>2</b>	Fixed to the lowest range	
		<b>3</b>	Fixed to the middle range	
		<b>4</b>	Fixed to the highest range	
<b>Cond</b> Response		<b>0</b>	Fast / sensitive	Software filtering
		<b>1</b>		
		♦ <b>2</b>		
		<b>3</b>	Slow / stable	
		<b>4</b>		
<b>st-b</b> Stability band width		<b>0</b>	Stable when within $\pm 0.5d/0.5s$	Conditions to turn on the stability mark
		♦ <b>1</b>	Stable when within $\pm 1d/0.5s$	
		<b>2</b>	Stable when within $\pm 2d/0.5s$	
<b>trc</b> Zero tracking		<b>0</b>	Disabled	Tracking zero shift
		♦ <b>1</b>	Enabled	
<b>pnt</b> Decimal point		♦ <b>0</b>	Point (.)	Decimal separator
		<b>1</b>	Comma (,)	
<b>Cp</b> Comparator mode		♦ <b>0</b>	Comparator disabled	Conditions to compare. d = the minimum display division
		<b>1</b>	Compares all data	
		<b>2</b>	Compares all stable data	
		<b>3</b>	Compares plus data > +4d	
		<b>4</b>	Compare stable plus data > +4d	
		<b>5</b>	Compares data > +4d or < -4d	
		<b>6</b>	Compares stable data > +4d or < -4d	
<b>bep</b> Buzzer output		♦ <b>0</b>	Buzzer does not sound.	Buzzer sounds according to the comparator results
		<b>1</b>	Buzzer sounds at LO.	
		<b>2</b>	Buzzer sounds at OK.	
		<b>3</b>	Buzzer sounds at OK and LO.	
		<b>4</b>	Buzzer sounds at HI.	
		<b>5</b>	Buzzer sounds at HI and LO.	
		<b>6</b>	Buzzer sounds at HI and OK.	
		<b>7</b>	Buzzer sounds at HI, OK and LO.	
<b>pnt</b> Data output mode		<b>0</b>	Command and stream modes	Auto-print A: + data Auto-print B: +/- data
		♦ <b>1</b>	Command and PRINT key	
		<b>2</b>	Command, PRINT key and auto-print A	
		<b>3</b>	Command, PRINT key and auto-print B	
<b>pUse</b> Data output pause		♦ <b>0</b>	No pause (general equipment)	Interval between continuous data
		<b>1</b>	1.6 seconds (for AD-8121)	
<b>info</b> GLP output		♦ <b>0</b>	No output	GLP output format
		<b>1</b>	AD-8121 format	
		<b>2</b>	General format	
<b>bps</b> Baud rate		♦ <b>0</b>	2400 bps	
		<b>1</b>	4800 bps	
		<b>2</b>	9600 bps	

♦ Factory setting

Class	Item	Parameter	Description
<b>func</b>	<b>btpr</b> Data and parity	♦ <b>0</b>	7 bits, even parity
		<b>1</b>	7 bits, odd parity
		<b>2</b>	8 bits, non parity
	<b>aCai</b>	<b>0</b>	ACAI disabled

	ACAI function	◆ <b>1</b>	ACAI enabled	no additional samples required.
	<b>Umi n</b> Minimum unit weight	◆ <b>0</b> <b>1</b> <b>2</b>	1 d 1/8 d total sample weight $\geq 5d^{(*)}$	d = the minimum display division
	<b>smpl</b> Sample number	◆ <b>0</b> <b>1</b> <b>2</b> <b>3</b> <b>4</b>	10 pcs 25 pcs 50 pcs 100 pcs 5 pcs	The number of samples shown first when entered into the unit weight storing mode
	<b>Idi n</b>	Not used (settings are not important)		
	<b>ItUp</b> LCD Backlight control	<b>0</b> <b>1</b> <b>2</b> ◆ <b>3</b> <b>4</b> <b>5</b>	Always off Turns off after 3 seconds Turns off after 10 seconds Turns off after 30 seconds Turns off after 60 seconds Always on	To control how the LCD backlight turns off. Weight change or key operation will turn the backlight on.
<b>CpHi</b>	Comparator upper limit	Setting the upper limit value		See
<b>Cplo</b>	Comparator lower limit	Setting the lower limit value		"6. COMPARATOR"
<b>Unit</b>	Weighing units to be displayed	Sets to display units		See "8-4. Storing weighing units"
<b>id</b>	ID number for GLP output	Sets the ID number		See "10. ID NUMBER AND GLP"

◆ Factory setting

(\*) Even if the weight display is "5d", there may be a range that it is not accepted. This is because the weight display data is rounded off internally.

---

## 9. RS-232C SERIAL INTERFACE


---

This interface allows the EK/EW-*i* series to be connected with a multifunction printer or a personal computer.

- ❑ The RS-232C interface has the following four modes.
  - Stream mode            Outputs data continuously.
  - Key mode                Outputs data by pressing the **PRINT** key.
  - Auto-print mode        Outputs data which meets the conditions of auto-print.
  - Command mode         Controls the balance using commands from a computer.
- ❑ Set the parameters of the data format (bps and btpr) and data output mode (prt), as necessary.
- ❑ Use a D-sub 9 pin cable (straight type) to connect with a computer.


## 9-1. Interface specifications

Transmission system	EIA RS-232C
Transmission form	Asynchronous, bi-directional, half-duplex
Data format	Baud rate: 2400, 4800, 9600 bps
	Data: 7 bits + parity 1bit (even or odd) or 8 bits (non-parity)
	Start bit: 1 bit
	Stop bit: 1 bit
	Code: ASCII
	Terminator: C <sub>R</sub> L <sub>F</sub> (C <sub>R</sub> : 0Dh, L <sub>F</sub> : 0Ah)




### Pin connections

D-sub 9pin male connector



Inside of the EK/EW-i

## 9-2. Data format



Separator 22

(" " shows a space.)



- ❑ There are four types of headers:
  - ST : Stable weighing data (including % data)
  - QT : Stable counting data
  - US : Unstable weighing data (including count and %)
  - OL : Out of weighing range (Over)
- ❑ The data is normally 9 digits including a decimal point and a sign.
- ❑ There are 11 types of units:
  - └└ g : Weighing data “gram”
  - └ P C : Counting data “pcs”
  - └└ % : Percentage data “%”
  - └ o z : Weighing data “decimal ounce”
  - └ l b : Weighing data “decimal pound”
  - o z t : Weighing data “troy ounce”
  - └ c t : Weighing data “carat”
  - mom : Weighing data “momme”
  - d w t : Weighing data “penny weight”
  - └GN : Weighing data “grain”
  - └ t l : Weighing data “tael”
- ❑ The terminator is always C<sub>R</sub>L<sub>F</sub>.

- ❑ Example of output data:

Weighing data “gram”	S	T	,	+	0	0	1	2	3	4	.	5	└	└	g	C <sub>R</sub>	L <sub>F</sub>
Counting data	Q	T	,	+	0	0	0	1	2	3	4	5	└	P	C	C <sub>R</sub>	L <sub>F</sub>
Percentage data	S	T	,	+	0	0	0	1	2	3	.	4	└	└	%	C <sub>R</sub>	L <sub>F</sub>
Out of range “gram” (+)	O	L	,	+	9	9	9	9	9	9	.	9	└	└	g	C <sub>R</sub>	L <sub>F</sub>
Out of range “pcs” (-)	O	L	,	-	9	9	9	9	9	9	9	9	└	P	C	C <sub>R</sub>	L <sub>F</sub>

### 9-3. Data output mode

#### Stream mode

Set the function “prt 0”.

The balance outputs the current display data. The data-update rate is approximately 10 times per second. This rate is the same as the display-update.

The balance does not output data while it is in the setting mode.

#### Key mode

Set the function “prt 1, 2 or 3”.

When the **PRINT** key is pressed while the weighing data is stable (the stability mark is on), the balance transmits the data. When the data is transmitted, the display will blink one time.

### Auto-print mode A

Set the function "prt 2".

The balance transmits the weighing data when the display is stable (the stability mark is on) and the data is greater than +4d (of the lowest range for EW-i series).

The next output can be obtained after the display returns below +4d.

### Auto-print mode B

Set the function "prt 3".

The balance transmits the weighing data when the display is stable (the stability mark is on) and the data is greater than +4d (of the lowest range for EW-i series) or less than -4d.

The next output can be obtained after the display returns between -4d and +4d.

## 9-4. Command mode

In the command mode, the balance is controlled by commands that come from the personal computer and so on.

### Command list

- ❑ Command to request the current weighing data.

Command 

Q	C <sub>R</sub>	L <sub>F</sub>
---	----------------	----------------

Reply 

S	T	,	+	0	0	1	2	3	4	.	5	_	_	g	C <sub>R</sub>	L <sub>F</sub>
---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	----------------	----------------

- ❑ Command to zero or tare the balance (same as the 

RE-ZERO
---------

 key).

Command 

Z	C <sub>R</sub>	L <sub>F</sub>
---	----------------	----------------

Reply 

Z	C <sub>R</sub>	L <sub>F</sub>
---	----------------	----------------

- ❑ Command to change the weighing units (same as the 

MODE
------

 key).

Command 

U	C <sub>R</sub>	L <sub>F</sub>
---	----------------	----------------

Reply 

U	C <sub>R</sub>	L <sub>F</sub>
---	----------------	----------------

---

## 10. ID NUMBER AND GLP

---

The ID number is used to identify the balance when Good Laboratory Practice (GLP) is used. The following GLP data is transmitted to an AD-8121 printer or a computer using the RS-232C interface.

- The result of calibration (“Calibration report”)
- The result of calibration test (“Calibration test report”)
- The “Start block” and “End block” for GLP data

## 10-1. Setting the ID number

1. Press and hold the **SAMPLE** key to display **func**.



**func**

2. Press the **SAMPLE** key several times to display **id**.



**id**

3. Press the **PRINT** key. Enter the ID number using the following keys.



**000000**

**SAMPLE** key To select the digit blinking to change.

**RE-ZERO** key To set the character of the digit selected. See the table below for the “display character set”.

**PRINT** key To store the value and proceed to the next step.

**MODE** key To cancel the value and proceed to the next step.


Set using the relevant keys

**end**

4. When the above operation has completed, **func** appears after **end**.

**func**

5. Press the **MODE** key to return to the weighing mode.



Returns to the weighing mode

### Display character set

0	1	2	3	4	5	6	7	8	9	-	_	A	B	C	D	E	F	G	H	I	J	K	L	M	N	O	P	Q	R	S	T	U	V	W	X	Y	Z
0	1	2	3	4	5	6	7	8	9	-	_	a	b	c	d	e	f	g	h	i	j	k	l	m	n	o	p	q	r	s	t	U	v	w	x	y	z

“\_” : Space

## 10-2. Output example

### Data format for “calibration report”

AD-8121 format “info 1”

```

Manufacturer  A & D
MODEL        EK 1201
S/N          1234567
ID           ABCDEF
DATE         02.05.14
  
```


← Manufacturer →  
 ← Model →  
 ← Serial number →  
 ← ID number →  
 ← Date →

General format “info 2”


```

.....A & D<CRLF>
MODEL.....EK-1201<CRLF>
S/N.....1234567<CRLF>
ID.....ABCDEF<CRLF>
DATE<CRLF>
  
```

Data format for "calibration test report"



"Start block" and "End block"



DOMINIQUE DUTSCHER SAS

### 10-3. Output procedure for the “Calibration report”

The function setting: “info 1” or “info 2” selected.

1. Press and hold the calibration (CAL) switch.  
Release the CAL switch when  is



Press and hold the CAL switch.

Cal

Release the CAL switch

Cal 0


Operation of Calibration  
(See “7.CALIBRATION”)

end

gl p

To output calibration report

end



Returns to the weighing mode

displayed.  
The balance starts calibration.  
For details on calibration, see “7. CALIBRATION”

2.  appears when the calibration has been completed.
3.  is displayed and calibration report is output.
4.  appears again. Remove the weight and press the  key to return to the weighing mode.


#### 10-4. Output procedure for the “Calibration test report”

The function setting: “i nfo 1” or “i nfo 2” selected.

The calibration test mode is used to confirm accurate weighing.



Press and hold  
the CAL switch.



1. Press and hold the calibration (CAL) switch.  
CC appears after Cal. Release the switch when CC is displayed.


2. CC 0 is displayed.

3. Press the SAMPLE key and change the weight value using the following keys.

SAMPLE key      To select the digit blinking to change.

RE-ZERO key      To set the value of the digit selected.

PRINT key      To store the value and return to step 2.



020000




CC 0

4. At step 2, press the PRINT key. The zero point is weighed and the weighed value is displayed for a few seconds.

5. Place a weight, of the same value as displayed, on the pan. Press the PRINT key to weigh it. The weighed value is displayed for a few seconds.

20000



6.  appears.

7.  is displayed and calibration test report is output.

8.  appears again. Remove the weight and press the  key to return to the weighing mode.




## 10-5. Output procedure for the “Start block” and “End block”

The function setting: “i nfo 1” or “i nfo 2” selected.

### Start block

1. Press and hold the  key. Release the





**PRINT** key when **start** is displayed. The balance outputs the Start block.

2. The balance can output the weighing data by pressing the **PRINT** key or selecting the auto-print mode.

### End block

3. Press and hold the **PRINT** key. Release the **PRINT** key when **reend** is displayed. The balance outputs the End block.
4. **end** appears. Press the **MODE** key to return to the weighing mode.

---

## 11. OPTIONS

---

The following options are available for the EK/EW-*i* series:

- OP-04 Comparator relay output and buzzer
- OP-07 Underhook assembly for EK-6000*i*, EK-12Ki and EW-12Ki
- OP-09 Rechargeable battery pack (Ni-MH)

- ❑ OP-12 Carrying case


## 11-1. OP-04 Comparator relay output and buzzer

Allows output of the HI, OK or LO signal results to an external device as a solid state relay output.

It is possible to sound a buzzer according to the comparison result. See the function “bep” to set which result will make a buzzer sound.

- ❑ **The comparator function on/off, the comparison mode and comparator buzzer output can be selected using the function settings. See the settings “cp” and “bep”.**
- ❑ **OP-04 cannot be used together with OP-09.**

### Output circuit




### Maximum rating

The maximum rating of the relay output is as follows.

- ❑ Maximum voltage: 50V DC
- ❑ Maximum current: 100mA DC
- ❑ Maximum ON resistance: 8Ω

### OP-04 Installation

1. Remove the cover of the option slot on the rear of balance by pressing and lowering it down.
2. Insert the option into the slot and secure it with the screws attached.




## 11-2. OP-07 Underhook assembly

By attaching the underhook assembly to the bottom of the balance, large objects that are difficult to load on the weighing pan can be weighed in suspension, and the specific gravity of objects may be measured.

- OP-07 is available for use with the EK-6000i / 12Ki and EW-12Ki balances only.**
- The calibration with a weight being hung on the hook is required for an accurate weighing.**

### OP-07 Installation

Remove the cover on the bottom of the balance, and screw the underhook assembly into the mounting hole.



## 11-3. OP-09 Rechargeable battery pack (Ni-MH)

By installing the rechargeable battery pack (Ni-MH) into the balance, cordless operation can be carried out for approximately 9 hours (used with the LCD backlight off).

- OP-09 cannot be used together with OP-04.**
- The battery life will vary depending on how the balance is used, ambient temperature and so on.**

## Charging the battery pack

Connect the AC adapter to the balance and turn the power off, then charging starts. It will take approximately 15 hours to reach full charge.

- If “1b0” is displayed when using the battery pack, immediately stop using it, and recharge the battery pack or use the AC adapter.*
- Charge the battery pack at a temperature between 0°C (32°F) and 40°C (104°F).*
- Do not charge too long. Overcharging will reduce the life of the batteries.*
- Be sure to charge the battery pack when using for the first time or if it has not been used for a long time (more than one month). Recharging two or three times may be needed to reach full charge.*
- Be sure to use only the AC adapter that is provided with the EK/EW-i balance.*

## OP-09 Installation

See the OP-04 installation.

## 11-4. OP-12 Carrying case

OP-12 is available for the convenience of carrying the balance by hand. However, note that because these balances are precision equipment, they will not be able to withstand excessive shock, such as being dropped.

---

# 12. MAINTENANCE

---

## 12-1. Notes on maintenance

- Do not disassemble the balance. Contact your local A&D dealer if your balance needs service or repair.
- Please use the original package for transportation.
- Do not use organic solvents to clean the balance. Use a warm lint free cloth

dampened with a mild detergent.

## 12-2. Error codes

### Overload error

e

Warning to indicate that an object beyond the balance capacity has been placed on the pan. Remove the object from the pan.

### Range over notice

-e

This will be shown by the EW-*i* series when a weight beyond the range capacity is tared and removed from the pan. Press the **SAMPLE** key to change the weighing range or press the **RE-ZERO** key.

### Unit weight error

l o

The sample weight is too light to set the unit weight in the counting mode.

### Sample quantity notice

10 - pcs

25 - pcs

50 - pcs

100 - pcs

When sample weight is light and the counting error could become large, the balance will request you to use larger number of samples. Place the displayed number of samples on the pan and press the **PRINT** key to store the unit weight.

**Note: Pressing the **PRINT** key without adding samples may reduce counting accuracy.**

**Starting from the 100 samples, **100 -** may be displayed when the sample weight is light. This is for your notice and press the **PRINT** key without adding any samples.**

**When “aCai 0” (ACAI disabled) or “Uni n 2” is set, this notice is not shown.**

### CAL errors

Cal e

Warning to indicate that calibration has been canceled because the calibration weight is too heavy.

-Cal e

Warning to indicate that calibration has been canceled because the calibration weight is too light.

Check the weighing pan and the calibration weight. To return to the weighing mode, press the **MODE** key.

### Low battery

l b0

Warning to show that the battery pack (OP-09) is discharged. Immediately stop using it, and recharge or use the AC adapter.

### Stability error

error1

Warning to indicate that the weight value is not stable and the balance cannot display it. Prevent vibration and

drafts. Press the **MODE** key to return to the weighing mode.

If you cannot cancel an error or other errors occurred, request service from the store where you purchased the balance or from your local A&D dealer.

---

## 13. SPECIFICATIONS

---

### 13-1. EK-*i* series

MODEL	EK-120 <i>i</i>	EK-200 <i>i</i>	EK-300 <i>i</i>	EK-600 <i>i</i>
Weight capacity	120 g	200 g	300 g	600 g
Min. display "d"	0.01 g	0.01 g	0.01 g	0.1 g
No. of samples	5, 10, 25, 50 or 100 pieces			
Max. count *)	12,000 pcs	20,000 pcs	30,000 pcs	6000 pcs

Min. unit weight *)	0.01 g	0.01 g	0.01 g	0.1 g
Min. % display	0.1 %			
Min. 100 % weight	1 g	1 g	1 g	10 g
Repeatability (Std. deviation)	0.01 g	0.01 g	0.01 g	0.1 g
Linearity	±0.01 g	±0.01 g	±0.02 g	±0.1 g
Sensitivity drift	±20 ppm / °C (10°C~30°C / 50°F~86°F)			
Display	7 segment LCD display with backlight (Character height 16 mm)			
Display update	10 time per second			
Operating temp.	-10°C~40°C / 14°F~104°F, less than 85% R.H. (non-condensing)			
Power supply	AC adapter or optional Ni-MH battery pack			
Battery operation	Approximately 9 hours (backlight off)			
Weighing pan size	110 mm ø			133mm x 170mm
Weight (approximately)	1.1 kg	1.1 kg	1.1 kg	1.3 kg
Calibration weight (factory setting)	120 g	200 g	300 g	600 g

MODEL	EK-1200i	EK-2000i	EK-3000i	EK-6000i	EK-12Ki
Weight capacity	1200 g	2000 g	3000 g	6000 g	12 kg
Min. display "d"	0.1 g	0.1 g	0.1 g	1 g	1 g
No. of samples	5, 10, 25, 50 or 100 pieces				
Max. count *)	12,000 pcs	20,000 pcs	30,000 pcs	6000 pcs	12,000 pcs
Min. unit weight *)	0.1 g	0.1 g	0.1 g	1 g	1 g
Min. % display	0.1 %				
Min. 100 % weight	10 g	10 g	10 g	100 g	100 g
Repeatability (Std. deviation)	0.1 g	0.1 g	0.1 g	1 g	1 g
Linearity	±0.1 g	±0.1 g	±0.2 g	±1 g	±1 g
Sensitivity drift	±20 ppm / °C (10°C~30°C / 50°F~86°F)				
Display	7 segment LCD display with backlight (Character height 16 mm)				
Display update	10 time per second				
Operating temp.	-10°C~40°C / 14°F~104°F, less than 85% R.H. (non-condensing)				
Power supply	AC adapter or optional Ni-MH battery pack				
Battery operation	Approximately 9 hours (backlight off)				
Weighing pan size	133 mm x 170 mm				
Weight (approximately)	1.5 kg	1.5 kg	1.5 kg	1.5 kg	1.5 kg
Calibration weight (factory setting)	1200 g	2000 g	3000 g	6000 g	12 kg

\*) In case of "Unit n 0" (factory setting)

## 13-2. EW-i series

MODEL	EW-150i			EW-1500i			EW-12Ki		
Weight capacity	30g	60g	150g	300g	600g	1500g	3kg	6kg	12kg
Min. display "d"	0.01g	0.02g	0.05g	0.1g	0.2g	0.5g	1g	2g	5g
No. of samples	5, 10, 25, 50 or 100 pieces								
Max. count *)	15,000 pcs			15,000 pcs			12,000 pcs		
Min. unit weight *)	0.01 g			0.1 g			1 g		
Min. % display	0.1 %								
Min. 100 % weight	1 g			10 g			100 g		

Repeatability (Std. deviation)	0.01g	0.02g	0.05g	0.1g	0.2g	0.5g	1g	2g	5g
Linearity	±0.01g	±0.02g	±0.05g	±0.1g	±0.2g	±0.5g	±1g	±2g	±5g
Sensitivity drift	±20 ppm / °C (10°C~30°C / 50°F~86°F)								
Display	7 segment LCD display with backlight (Character height 16 mm)								
Display update	10 time per second								
Operating temp.	-10°C~40°C / 14°F~104°F, less than 85% R.H. (non-condensing)								
Power supply	AC adapter or optional Ni-MH battery pack								
Battery operation	Approximately 9 hours (backlight off)								
Weighing pan size	110 mm ø			133 mm x 170 mm					
Weight (approximately)	1.1 kg			1.5 kg			1.5 kg		
Calibration weight (factory setting)	150 g			1500 g			12 kg		

\*) In case of "Umi n 0" (factory setting)

### 13-3. Other weighing units

MODEL		EK-120i	EK-200i	EK-300i	EK-600i	EK-1200i	EK-2000i	EK-3000i	EK-6000i	EK-12Ki
oz.	Capacity	4.2330	7.0550	10.5820	21.165	42.330	70.550	105.820	211.65	423.30
	Min. display	0.0005	0.0005	0.0005	0.005	0.005	0.005	0.005	0.05	0.05
lb	Capacity	-----	-----	-----	1.3230	2.6455	4.4090	6.6140	13.230	26.455
	Min. display	-----	-----	-----	0.0005	0.0005	0.0005	0.0005	0.005	0.005
ozt	Capacity	3.8580	6.4300	9.6450	19.290	38.580	64.300	96.450	192.90	385.80
	Min. display	0.0005	0.0005	0.0005	0.005	0.005	0.005	0.005	0.05	0.05
ct	Capacity	600.00	1000.00	1500.00	3000.0	6000.0	10000.0	15000.0	-----	-----
	Min. display	0.05	0.05	0.05	0.5	0.5	0.5	0.5	-----	-----
mom	Capacity	32.000	53.335	80.000	160.00	320.00	533.35	800.00	1600.0	3200.0
	Min. display	0.005	0.005	0.005	0.05	0.05	0.05	0.05	0.5	0.5
dwt	Capacity	77.16	128.60	192.90	385.8	771.6	1286.0	1929.0	3858	7716
	Min. display	0.01	0.01	0.01	0.1	0.1	0.1	0.1	1	1
GN	Capacity	1851.8	3086.4	4629.8	9260	18518	30864	46298	-----	-----
	Min. display	0.2	0.2	0.2	2	2	2	2	-----	-----
tl	Capacity	3.1745	5.2910	7.9365	15.875	31.745	52.910	79.365	158.75	317.45
	Min. display	0.0005	0.0005	0.0005	0.005	0.005	0.005	0.005	0.05	0.05

#### □ Note

**The unit "tl (Hong Kong General / Singapore)" is for special versions only.**

MODEL		EW-150i			EW-1500i			EW-12Ki		
oz.	Capacity	1.0580	2.116	5.292	10.580	21.16	52.92	105.80	211.6	423.2
	Min. display	0.0005	0.001	0.002	0.005	0.01	0.02	0.05	0.1	0.2
lb	Capacity	-----	-----	-----	0.6615	1.323	3.306	6.615	13.23	26.46
	Min. display	-----	-----	-----	0.0005	0.001	0.002	0.005	0.01	0.02
ozt	Capacity	0.9645	1.929	4.822	9.645	19.29	48.22	96.45	192.9	385.8
	Min. display	0.0005	0.001	0.002	0.005	0.01	0.02	0.05	0.1	0.2
ct	Capacity	150.00	300.0	750.0	1500.0	3000	7500	-----	-----	-----
	Min. display	0.05	0.1	0.2	0.5	1	2	-----	-----	-----
mom	Capacity	8.000	16.00	40.00	80.00	160.0	400.0	800.0	1600	3200




	Min. display	0.005	0.01	0.02	0.05	0.1	0.2	0.5	1	2
dwt	Capacity	19.29	38.58	96.45	192.9	385.8	964.5	1929	3858	7715
	Min. display	0.01	0.02	0.05	0.1	0.2	0.5	1	2	5
GN	Capacity	463.0	926.0	2315	4630	9260	23150	-----	-----	-----
	Min. display	0.2	0.5	1	2	5	10	-----	-----	-----
tl	Capacity	0.7935	1.587	3.968	7.935	15.87	39.68	79.35	158.7	317.4
	Min. display	0.0005	0.001	0.002	0.005	0.01	0.02	0.05	0.1	0.2

□ **Note**

The unit "tl (Hong Kong General / Singapore)" is for special versions only.

### 13-4. Dimensions



EK-120i / EK-200i / EK-300i

EW-150i

EK-600i / EK-1200i / EK-2000i


EK-3000i / EK-6000i / EK-12Ki

EW-1500i / EW-12Ki

## GRAVITY ACCELERATION MAP

### Values of gravity at various locations

Amsterdam	9.813 m/s <sup>2</sup>	Manila	9.784 m/s <sup>2</sup>
Athens	9.807 m/s <sup>2</sup>	Melbourne	9.800 m/s <sup>2</sup>
Auckland NZ	9.799 m/s <sup>2</sup>	Mexico City	9.779 m/s <sup>2</sup>
Bangkok	9.783 m/s <sup>2</sup>	Milan	9.806 m/s <sup>2</sup>
Birmingham	9.813 m/s <sup>2</sup>	New York	9.802 m/s <sup>2</sup>
Brussels	9.811 m/s <sup>2</sup>	Oslo	9.819 m/s <sup>2</sup>



DOMINIQUE DUTSCHER SAS

MEMO

---

---

---

---

---

---

---

---

DOMINIQUE DUTSCHER SAS

MEMO

DOMINIQUE DUTSCHER SAS

MEMO

DOMINIQUE DUTSCHER SAS

# **AND**

## **A&D Company, Limited**

3-23-14 Higashi-Ikebukuro, Toshima-ku, Tokyo 170-0013 JAPAN  
Telephone: [81] (3) 5391-6132 Fax: [81] (3) 5391-6148

## **A&D ENGINEERING, INC.**

1555, McCandless Drive, Milpitas, CA. 95035 U.S.A.  
Telephone: [1] (408) 263-5333 Fax: [1] (408) 263-0119

## **A&D INSTRUMENTS LTD.**

Unit 24/26 Blacklands Way, Abingdon Business Park, Abingdon, Oxon OX14 1DY United Kingdom  
Telephone: [44] (1235) 550420 Fax: [44] (1235) 550485

## **<German Scales Office>**

Berner StraÙe 64, 60437 Frankfurt/Main 50 GERMANY  
Telephone: [49] (69) 507-1017 Fax: [49] (69) 507-2054

## **A&D MERCURY PTY. LTD.**

32 Dew Street, Thebarton, South Australia 5031 AUSTRALIA  
Telephone: [61] (8) 8352-3033 Fax: [61] (8) 8352-7409

## **A&D KOREA Limited**

8th Floor, Manhattan Bldg. 36-2 Yoido-dong, Youngdeungpo-ku, Seoul, KOREA  
Telephone: [82] (2) 780-4101 Fax: [82] (2) 782-4280